Gas and Electric



Tips and fixes

EDMI Smart Meter





utilita.co.uk

UDE_CX_UG_EDMI January 2023 – Version 1.0 Utilita Energy Limited Copyright 2023 Registered in England & Wales, Company Number 04849181, Regulated by Ofgem Utilita Energy Limited, Hutwood Court, Bournemouth Rd, Chandler's Ford, Eastleigh SO53 3QB

Electric Smart Meter



Restoring your supply

Make sure you turn off all your appliances before your restore supply. You'll also need to make sure you've got a positive balance.

- Once topped up, press and hold the OK button.
- Press and hold the OK button again to go to the Prepay screen.
- Scroll through the screens using the OK button until you get to 'Info-Supply'. Then press and hold the OK button.
- Press and hold the OK button again to re-enable supply.

You should have restored your supply.

Checking your balance

 Press and hold the OK button to view your balance.

Manually enter a top-up

- ✓ Press the OK button.
- Press and hold the OK button again to enter the Prepay screen.
- Press and hold the OK button again to enter Prepay Top-up screen.
- Enter your top-up code (UTRN) you can use the arrows to select the digits. The OK button will move to the next digit.
- Press and hold OK to confirm your top-up code.

If you enter any information incorrectly, just press and hold RETURN to go back and change the number you entered.

Activating Emergency Credit

You can activate Emergency Credit when your meter balance is low and you're struggling to top-up. Emergency Credit is available when the 'E' icon is lit.

 Press and hold the return button to accept Emergency Credit.

Don't forget – you'll need to pay back any Emergency Credit you use. Make sure the meter is topped-up by at least £1 so you don't go off-supply. For example, if you've used £3 of Emergency Credit, then you'll need to top-up at least £4.

View any debt

- Press and hold the OK button.
- Press and hold the OK button again to enter the prepay screen.
- Press the OK button to scroll through to find the Prepay Debts screen. Press OK to select.
- Press the OK button until you find the Debts Total screen.
- Press and hold the OK button to view your total debt – this is the full amount you owe.

If you're struggling to top-up or keep on top of your energy costs, we've got loads of advice and support over on our online Help Centre. Visit <u>utilita.co.uk/help</u>

View your tariff

- Press and hold the OK button.
- Press and hold the OK button again to enter the Tariffs screen.
- ✓ Press the **OK** button to find the Tariff Now screen.
- Press and hold the OK button to access the Price screen.

View your meter reading

Press the **OK** button to check your meter reading. The number below 'IMPORT' on the first screen is your meter reading.

Gas Smart Meter



Restoring your supply

Make sure all gas appliances are off and disconnected before restoring your supply.

- When your meter says 'Supply Armed', press and hold the OK button to restore your supply.
- ✓ You should have restored your supply.

Checking your balance

 Press and hold the OK button to view your balance – the screen will switch between balance and usage.

Manually enter a top-up

- Press and hold the OK button to access the main menu.
- ✓ Use the **OK** button to show the Prepay Menu.
- ✓ Press and hold **OK** to show the Top Up screen.
- Press and hold OK again.
- Use the OK button to select the digits of your top-up code (UTRN). Press and hold OK to move to the next digit.
- Press and hold OK after you've entered your last digit to confirm the top-up code.
- If you enter any information incorrectly, just press and hold RETURN to go back and change the number you entered.

The screen will show a message to confirm whether your top-up was successful.

Activating Emergency Credit

You can activate Emergency Credit when your meter balance is low and you're struggling to top-up.

- ✓ Press and hold **OK** to wake up your meter.
- Press and hold the Return button to activate Emergency Credit.

Don't forget – you'll need to pay back any Emergency Credit you use. Make sure the meter is topped-up by at least £1 so you don't go off-supply. For example, if you've used £3 of Emergency Credit, then you'll need to top-up at least £4.

View any debt

- Press and hold OK to go to the menu use OK to get to the Prepay Menu.
- Press and hold the OK button until the screen show Debts.
- Press and hold the OK button again to show Total Debt.

If you're struggling to top-up or keep on top of your energy costs, we've got loads of advice and support over on our online Help Centre. Visit <u>utilita.co.uk/help</u>

View your tariff

- ✓ Press the OK button to access the main menu.
- Press and hold the OK button again to go to Prepay Menu.
- Press the arrow buttons to find Tariffs.
 Press OK to confirm this.
- Press the arrow button until you reach the NOW screen.
- Press OK to view your prices.

View your meter reading

Press the **OK** button to check your meter reading (you can ignore any numbers after the decimal point).